

VG-6737 Digital Sounder Beacon

P-Code: 010101012

V-GREAT GLOBAL CORPORATION

Second Floor, Capital City, Independence Avenue, P.O. Box 1008, Victoria, Mahe, Seychelles

FEATURES

- * Electronic addressing
- * Sound or Beacon switchable
- * Sixteen alert tones available
- * Four volume settings
- * Loop powered or external power supply
- * Device locking facility
- * Talented plug-in structure without screw
- * LPCB approval to EN54-3






DESCRIPTION


VG-6737 Digital Sounder Beacon, as a warning device, combined flashlight and sound, is fully compatible with Digital Protocal and Intelligent Protocal. Each beacon contains sixteen alert tones and four levels of volume, but occupy only one address. With a unique design, it can be directly connected in the loop and driven by loop-power, as well as external power supply. This beacon is automatically activated or restored when a fire situation is detected or removed, or manually controlled on FD&A panel. VG-6737 is suitable for the applications of visual or audible warning or both required for the purpose of evacuation.


DIMENSION





WIRING INSTRUCTION





TECHNICAL DATA

Operating Voltage	16VDC-28VDC	Alarm Tone	16 types
Alarm Current	<8 mA	IP Rating	21C
Standby Current	<0.3mA	Humidity	≤95%RH, (40±2°C) non-condensing
Temperature range	-10℃~50℃	Weight	About 120g
Alarm Volume	4 levels	Base	VG-6619